

Channels	1
Input type	1 x Potentiometer
Input	3-wire potentiometer (1-100k Ω TYPICAL)
Excitation	+2.5V (10mA MAX)
Resolution	1:100,000 counts OF FS (+2.5V)
Zero drift	$\pm 40\mu\text{V}/^\circ\text{C}$ TYPICAL
Span drift	$\pm 5\text{ppm}/^\circ\text{C}$ OF FS
Non-linearity	$\pm 0.003\%$ OF FS
Output rate	1-60Hz output (all channels)
Rejection <i>SELECT</i>	50/60Hz

- High speed, high accuracy potentiometer - ideal for linear displacement applications